

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
4 March 2004 (04.03.2004)

PCT

(10) International Publication Number
WO 2004/019259 A1

(51) International Patent Classification⁷: G06K 7/00

(21) International Application Number:
PCT/EP2003/008877

(22) International Filing Date: 8 August 2003 (08.08.2003)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
02292063.1 21 August 2002 (21.08.2002) EP

(71) Applicant (for all designated States except US): THOMSON LICENSING S.A. [FR/FR]; 46 Quai A. le Gallo, F-92100 Boulogne-Billancourt (FR).

(72) Inventor; and

(75) Inventor/Applicant (for US only): BERTIN, Jean-Pierre [FR/FR]; 31bis Boulevard de Courcelles, F-44290 Guemene-Penfao (FR).

(74) Agent: ARNOLD, Klaus-Peter; European Patent Operations, Karl-Wiechert-Allee 74, 30625 Hannover (DE).

(81) Designated States (national): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.


(84) Designated States (regional): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:

- with international search report
- before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: APPLIANCE WITH AN IC CARD READER AND OVERLOAD PROTECTION



(57) Abstract: The appliance comprises an IC card reader (3) for an operation with an IC card and a power supply (4) for providing a supply voltage (VCC), in particular for the IC card. The appliance comprises further an overload protection circuit (6), which simulates an IC card extraction in case of an overload of the supply voltage. The power supply (4) is then immediately switched off to avoid any damage for the power supply. In a preferred embodiment, the IC card reader (3) is equipped with a card presence switch (2) for indicating to a micro-controller (5) of the appliance, that an IC card has been inserted into the card reader. The micro-controller provides then a control signal for switching on the power supply for the operation with the IC card. The protection circuit (6) is coupled between the supply voltage for the IC card and the signal line of the card presence switch and provides a detection of a short circuit. The protection circuit may comprise a diode, a comparator or a transistor, which switches off the power supply (4) via a logic circuit (IC3).

Appliance with an IC Card Reader and Overload Protection

The present invention relates to an appliance having an IC card reader for operation with an IC card. Appliances of this kind are known for example from pay television broadcast (pay TV), electronic payment, or banking services.

IC cards, also known as smart cards, are portable information media, having the size of about a credit card. They comprise an integrated card controller, or at least an integrated memory, for a data exchange with a respective appliance. A portable device of this kind is known for example from EP-A-0 633 544. As a general term for this data media the expression "IC card" will be used throughout in this description. IC cards are usually provided with contacts being mechanically contacted by an IC card reader for an electrical connection for the data exchange with the respective appliance.

The communication between IC cards and respective appliances with IC card readers is described for example in WO 97/25685 and EP-A-0 814 427. An international standard, which describes and defines IC cards having contacts and the operation procedures of IC cards, is ISO/IEC 7816-3:1997(E). This standard is used particularly for pay television systems, which use a set-top box or a digital satellite receiver with an IC card reader and respective IC cards for authorizing the reception of pay television broadcasts. The respective IC cards comprise data, which enable the set-top box to unscramble received coded video signals.

In appliances using an IC card reader, there is a possibility that a short circuit occurs, when inserting the IC card into the card reader, for example when the IC card is damaged, or when there is moisture on the IC card. Standards like ISO/IEC 7816 or EMV2000 require therefore a

protection of the supply voltage against short circuits. A widely used interface IC TDA8004, made for example by Philips Semiconductors, has therefore a short circuit protection already included. This integrated circuit provides many functions and is therefore comparatively expensive.

An overcurrent protection circuit for a power supply providing an IC card with power is disclosed in US 5,977,758. This circuit comprises a current detection circuit, which switches in case of a malfunction the power to the IC card off independently of a micro-controller.

It is an object of the invention to provide an appliance having an IC card reader and an overload protection, which provides a high reliability.

This object is achieved by an appliance as specified in claim 1. Advantageous developments of the invention are specified in the subclaims.

According to the invention, the appliance comprises an IC card reader for an operation with an IC card and a power supply for providing a supply voltage, in particular for the IC card reader. The appliance comprises further an overload protection circuit, which simulates an IC card extraction in case of an overload of the supply voltage. The power supply is then immediately switched off to avoid any damage for the power supply.

In a preferred embodiment, the IC card reader is equipped with a card presence switch for indicating to a micro-controller of the appliance, that an IC card has been inserted into the card reader. The micro-controller provides then a control signal for switching on the power supply for the operation with the IC card. Power to the IC card is therefore only provided, when a signal of the card presence switch indicates that an IC card has been

inserted. In case of an overload of the supply voltage, the overload protection circuit changes the positive signal of the card presence switch to a value, which states that no IC card is present. Therefore, an extraction of the IC card
5 is simulated.

In a further preferred embodiment, the overload protection circuit is coupled between the supply voltage for the IC card and the signal line of the card presence switch and
10 provides a detection of a short circuit. The protection circuit may comprise a diode, a comparator or a transistor, which resets the value of the card presence switch to a value, which simulates that no IC card is present.

Advantageously, a logic circuit is used, to control the switching on and off of the power supply for the IC card. To this circuit the card presence signal and the power on/off signal from the micro-controller are coupled and the operation of the logic circuit is such, that the power
15 supply is only switched on, when an IC card is inserted applying a positive signal from the card presence switch to the logic circuit, and when the micro-controller provides the command signal for switching on the supply voltage. Then the logic circuit switches through for turning the
20 power to the IC card on. The logic circuit is for example an AND circuit or a NAND circuit. When a short circuit occurs, the power to the IC card is immediately switched off via the logic circuit, independently from the micro-controller. The power is therefore switched off much
25 faster, as could be performed by the micro-controller, which reduces the danger of damaging the power supply.
30

Preferred embodiments of the invention are now explained in more detail with reference to schematic drawings, which
35 show:

Fig. 1 An appliance with an IC card reader and an overload protection circuit, and

Fig. 2 an appliance with an IC card reader comprising a protection circuit against a short circuit.

The appliance shown in Fig. 1 comprises an IC card reader 3, which is powered by a power supply 4 via line 8. The IC card reader 3 comprises in particular a housing, in which a respective IC card can be inserted, and contact terminals for applying a supply voltage VCC to the IC card and for providing an exchange of digital data between the IC card and a micro-controller 5 of the appliance. The card reader 3 comprises further a card presence switch 2, which provides a signal "CARD-DET" via a signal line 7 to the micro-controller 5, when an IC card is inserted. The card presence switch 2 is a mechanical switch, which is operated, when an IC card is inserted. If an IC card is inserted, the switch 2 is opened. Via a respective circuitry, as explained with regard to Fig. 2, a logical "HIGH" signal, "CARD-DET", is provided then to the micro-controller 5.

According to the invention, an overload protection circuit 6 is coupled between the line 8 of the supply voltage VCC and the line 7 of the card detect signal, which converts in case of an overload of the supply voltage VCC the signal indicating the presence of an inserted IC card to a value, which states that no IC card is present. The overload of the supply voltage VCC simulates therefore via the protection circuit 6 an IC card extraction for switching off the power supply 4.

The power supply 4 in this embodiment is switched on and off by a logic circuit IC3, to which inputs the signal from the card presence switch 2 "CARD-DET" is applied and the power on/off signal "CMD-VCC" from the micro-controller 5. The power supply 4 is then switched on only, when a positive signal from the card presence switch 2 is provided and a power on command from the micro-controller 5. In case of an overload condition, the protection circuit 6 converts

the signal from the card presence switch 2 from "CARD DETECTED" to "NO CARD PRESENT", and therefore switches off the power supply 4 immediately via the logic circuit IC3. The logic circuit IC3 is for example a NAND or an AND
5 circuit.

The protection circuit 6 may comprise an over-current protection circuit, which measures the current of line 8 for example via a measuring resistor, and which provides a
10 respective signal for an overload, when the current provided by the power supply 4 is too high. In another embodiment, the protection circuit 6 comprises a voltage detector for the supply voltage VCC, which uses a voltage threshold for determining a breakdown of the supply voltage
15 VCC. This can be performed for example by a protection circuit comprising a comparator, a transistor or a diode, or by any other switching element. A supply voltage breakdown occurs for example in case of a short circuit.

20 In Fig. 2 a detail of a digital set-top box is shown comprising an IC card reader 3 and relevant parts for the operation of the set-top box with an IC card. The IC card reader 3 comprises an IC card connector 1 with contacts C1 - C8, for operation with an IC card according to the IEC
25 7816-3:1997(E) standard. The contacts C1 - C8 provide the following connections to an IC card: C1 for supply voltage VCC, C2 for a reset of the IC card, C3 for providing a clock signal CLK to the IC card, C4, C5 and C8 for providing ground terminal connections to the IC card, C6
30 (reserved for a programming voltage VPP) and C7 for providing a data input/output connection for a data exchange between the IC card and the set-top box.

The set-top box comprises further an integrated circuit
35 IC1, a buffer and line driver for the digital signals used for operation with the IC card. The respective signals, which are coupled to the integrated circuit 1, are the reset signal "RESET-CARD" for contact C2, the clock signal

"CLK-CARD" for contact C3, and data input and output signals "DOUT" and "DIN" for contact C7. The integrated circuit IC1 is for example an integrated circuit 74HCT244 from Texas Instruments. For the IC1, also for the IC card and the electronics of the IC card reader 4, a supply voltage of 5 Volts is used.

The IC card reader 3 comprises a card presence switch 2 with switch contacts SW for a detection of an IC card, when an IC card is inserted into the IC card connector 1. To one of the switch contacts, PRES, a supply voltage of 5 V is coupled via a resistor R1. When an IC card is inserted into the IC card connector 1, the switch contacts SW are open. Also a transistor T1 is coupled via its base terminal to the switch contact PRES. The transistor T1 provides therefore a "LOW" output signal, when the switch 2 is open, (IC card inserted) and a "HIGH" output signal, when the switch 2 is closed.

To the transistor T1 a NAND circuit IC2 is coupled, which is arranged as an inverter, for providing a signal "CARD-DET" for a micro-controller, not shown in Fig. 2, of the set-top box. The micro-controller is for example a "system-on-chip" controller STI5516 from ST Microelectronics. The output signal of the NAND circuit IC2 is therefore "HIGH", when an IC card is inserted. The output of IC2 is also coupled to an input of a NAND circuit IC3, for providing a supply voltage VCC to the IC card, terminal C1. To the other input of the NAND circuit IC3 a control signal "CMD-VCC" from the micro-controller is coupled. Therefore, when an IC card has been inserted and then the control signal "CARD-DET" is provided, the micro-controller provides the signal "CMD-VCC" for switching on the supply voltage VCC for the IC card. The supply voltage VCC is provided by a transistor T2, to which base terminal the output of IC3 is coupled. When the output of the NAND gate IC3 switches to "LOW", transistor T2 switches through for supplying a 5 V

supply voltage VCC to the contact C1 of the IC card connector 1.

Between the line providing the supply voltage VCC to the
5 contact C1 and the line coming from the switch contact PRES
of card presence switch 2 a diode D1 is coupled, which is
arranged such, that the diode D1 conducts, when the signal
from the switch contact is "HIGH", but the supply voltage
VCC is low. Therefore, when the supply voltage VCC breaks
10 down when an IC card is inserted, for example when the IC
card has a short circuit between respective IC card
contacts, the diode D1 switches through and therefore
switches off transistor T1. Then the output of NAND circuit
IC2 switches to "LOW", which switches off immediately the
15 transistor T2 via NAND circuit IC3. The transistor T2, the
power supply for the IC card, is switched off therefore
immediately by transistor T1 and NAND circuits IC2 and IC3,
and will not be damaged by a short circuit. There is a much
smaller delay, as would be the case when the transistor T2
20 would be switched off via the micro-controller. The diode
D1 provides therefore a very effective short circuit
protection.

Instead of NAND circuits IC2 and IC3, also buffer/line
25 driver circuits with a controllable output can be used, for
example integrated circuits Quad buffer/line driver 74HC125
or 74HC126, manufactured for example from Philips
Semiconductors. These circuits comprise four non-inverting
buffers, which outputs are controllable via a respective
30 output enable input, the 74HC125 having active LOW enable
inputs and the 74HC126 active HIGH enable inputs.

The overload protection circuit 6, Fig. 1, may be arranged
also within a power supply circuit, which provides then an
35 error signal in case of an overload. For example, an
adjustable power voltage regulator LP2951 from Fairchild
Semiconductor Corporation can be used, which provides an
error signal in case of a low output voltage, which may

occur for example in case of a short. The IC LP2951 is switched on and off via the signal CMD-VCC from micro-controller 5, see Fig. 1.


- 5 The error signal from IC LP2951 can be applied for example to the output enable input of a buffer/line driver circuit, IC 74HC125, to which input the card detected signal CARD-DET, Fig. 1, is coupled, and which output is coupled to IC3 and to the micro-controller 5. In case of an overload of
10 the supply voltage VCC, the error signal from IC LP2951 then changes the output from the buffer/line driver circuit from positive to negative, simulating therefore an IC card extraction, which switches off the power supply 4 via IC3.
- 15 The overload protection as described is especially suited for a digital set-top box or a satellite receiver operating with an IC card, but applications for other appliances having an IC card reader for operation with an IC card are also possible. The appliance may have also further IC card
20 readers, which are protected in the same way.

Claims

1. Appliance comprising an IC card reader (3) and a power supply (4, T2) for providing a supply voltage (VCC),
5 **characterized in that** the appliance comprises an overload protection circuit (6, D1), which simulates an IC card extraction in case of an overload of the supply voltage (VCC).
- 10 2. Appliance according to claim 1, **characterized in that** the IC card reader (3) comprises a card presence switch (2), and that in case of an overload of a the supply voltage (VCC), the overload protection circuit (6, D1) changes a card detected signal (CARD-DET) from positive
15 to negative for simulating an IC card extraction.
3. Appliance according to claim 2, **characterized in that** the overload protection circuit (6, D1) is coupled to the card presence switch (2) and to the supply voltage
20 (VCC) for a detection of an overload of the supply voltage (VCC).
4. Appliance according to claim 3, **characterized in that** the overload protection circuit (6, D1) comprises a
25 diode (D1), a comparator or a switch, being arranged for detecting a voltage breakdown of the supply voltage (VCC).
5. Appliance according to one of the preceding claims,
30 **characterized in that** to inputs of a switching means (IC3) a card detected signal (CARD-DET) and a supply voltage "ON/OFF" command (CMD-VCC) provided by a micro-controller (5) is coupled, for switching on the power supply (4, T2) only, when the card detected signal
35 (CARD-DET) is positive.
6. Appliance according to claim 5, **characterized in that** the switching means (IC3) is a logic circuit gate, for

example a NAND or an AND circuit, or a buffer/line driver circuit with an output enable input.

- 5 7. Appliance according to claim 1, 5 or 6, **characterized in that** that the overload protection circuit (6) is arranged within the power supply circuit (4), which provides an error signal in case of an overload, and that in case of an overload of the respective supply voltage (VCC), the error signal changes via a logic
10 circuit a card detected signal (CARD-DET) from positive to negative for simulating an IC card extraction.
- 15 8. Appliance according to one of the preceding claims, **characterized in that** the supply voltage (VCC) is a supply voltage for the IC card reader (3), in particular for an IC card contact (C1).
- 20 9. Appliance according to one of the preceding claims, **characterized in that** the appliance is a digital set-top box or a digital satellite receiver with a respective IC card reader.






Fig. 2

INTERNATIONAL SEARCH REPORT

International Application No

PCT/EP 03/08877

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 G06K7/00

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 G06K

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data, PAJ

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	WO 97 23840 A (THOMSON CONSUMER ELECTRONICS) 3 July 1997 (1997-07-03) page 1, line 1 -page 5, line 5; figures 1-4	1,8,9
A	EP 0 363 871 A (OKI ELECTRIC INDUSTRY COMPANY) 18 April 1990 (1990-04-18) column 4, line 20 -column 8, line 6; figures 1,2	1,3,4,8
A	EP 0 862 261 A (TOSHIBA) 2 September 1998 (1998-09-02) the whole document	

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- *&* document member of the same patent family

Date of the actual completion of the international search

19 January 2004

Date of mailing of the international search report

29/01/2004

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Calarasanu, P

INTERNATIONAL SEARCH REPORT

International Application No

PCT/EP88/08877

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 9723840	A	03-07-1997	
		AU 1130497 A	17-07-1997
		AU 1150497 A	17-07-1997
		AU 1151997 A	17-07-1997
		AU 715450 B2	03-02-2000
		AU 1290897 A	17-07-1997
		AU 1417497 A	17-07-1997
		AU 1419997 A	17-07-1997
		AU 1424497 A	17-07-1997
		AU 1467397 A	17-07-1997
		BR 9612168 A	13-07-1999
		BR 9612170 A	13-07-1999
		BR 9612176 A	13-07-1999
		BR 9612205 A	13-07-1999
		CA 2240287 A1	03-07-1997
		CN 1209228 A	24-02-1999
		CN 1219304 A ,B	09-06-1999
		CN 1209209 A ,B	24-02-1999
		CN 1209242 A ,B	24-02-1999
		CN 1205821 A ,B	20-01-1999
		CN 1205785 A ,B	20-01-1999
		CN 1209243 A	24-02-1999
		CN 1209245 A	24-02-1999
		DE 69604596 D1	11-11-1999
		DE 69604596 T2	20-01-2000
		DE 69606783 D1	30-03-2000
		DE 69606783 T2	16-11-2000
		DE 69620023 D1	25-04-2002
		DE 69620023 T2	22-08-2002
		DE 69620630 D1	16-05-2002
		DE 69620630 T2	28-11-2002
		DE 69628671 D1	17-07-2003
		DE 69628671 T2	18-12-2003
		EP 0868688 A1	07-10-1998
		EP 0876724 A1	11-11-1998
		EP 0868807 A1	07-10-1998
		EP 0868704 A1	07-10-1998
		EP 0868782 A1	07-10-1998
		EP 0868781 A1	07-10-1998
		EP 0868805 A1	07-10-1998
		EP 0868810 A1	07-10-1998
		ES 2142630 T3	16-04-2000
		JP 2000502475 T	29-02-2000
		JP 2000502531 T	29-02-2000
		JP 2000505962 T	16-05-2000
		JP 2000502476 T	29-02-2000
		JP 2000516358 T	05-12-2000
		JP 2000513515 T	10-10-2000
		JP 2000505257 T	25-04-2000
		JP 2000502534 T	29-02-2000
		US 6134321 A	17-10-2000
EP 363871	A	18-04-1990	
		AU 624636 B2	18-06-1992
		AU 4268989 A	26-04-1990
		CA 1319987 C	06-07-1993
		EP 0363871 A2	18-04-1990
		NZ 230844 A	25-06-1992
		US 5034599 A	23-07-1991

INTERNATIONAL SEARCH REPORT

International Application No

PCT/EP 93/08877

Patent document cited in search report		Publication date		Patent family member(s)	Publication date
EP 862261	A	02-09-1998	JP	10243544 A	11-09-1998
			EP	0862261 A2	02-09-1998
			US	5977758 A	02-11-1999
<hr/>					